

Prepare the tap for installation

1. Remove hex port plugs and yellow port covers from the tap housing.
2. Loosen seizure screws.
3. Cut the connector pin to 1¹/₄ in. using the trim guide on the tap housing.
4. Install the front portion of the pin connector into the tap housing and hand tighten.
5. Complete tightening with an adjustable wrench for a 1/8 to 1/4 turn.
6. Tighten the seizure screws to 15 in-lbs.
7. Replace the hex port plugs and tighten to 45 in-lbs.

Direct Strand Mounting*

1. Loosen the strand clamp assembly and install on strand.
2. Slide shrink boot over cables if applicable.
3. Position cables and tighten strand clamp to 70 in-lbs.
4. Prep the cables for installation according to the manufacturer's specification.
5. Complete installation of the cable connector onto the 5/8 x 24 main cable ports by tightening according to the manufacturer's instruction.
6. If applicable, slide shrink boot over the entry connector until it touches main part of housing and shrink per manufacturer's guidelines.

Faceplate replacement

1. Disconnect all the house drops from the faceplate's F-ports.
2. Use a 5/16 nut driver to loosen all the bolts on the faceplate.
3. Firmly pull on the BOTTOM CENTER BOLT closest to the dB label to remove the faceplate.
4. Inspect the housing for debris, water migration and the rubber gasket's groove.
5. Inspect the replacement faceplate for proper RFI gasket and rubber gasket.
6. Firmly press the replacement faceplate into the housing.
7. Tighten the four faceplate bolts in the order numbered on the image below (bottom, then top, then left, then right) to 40 in-lbs.
8. Re-install the house drops to 30 in-lbs.

Material Requirements

Contents of Package

- MGT2000-SE-G2 Series Milenium Series Multi-tap

Tools and Hardware

Not Included

- Cable preparation/splicing tools
- Coaxial cable connector
- 5/16 nut driver
- 30 in. lb. torque wrench

*See www.antronix.com/resources for pedestal installation information.

